



Fan Pre-Selection Chart-Direct Drive

The Pre-Selection Chart Below Should be Used to Determinal Which Drive Arrangement Best Meets Design Requirements:
50Hz Direct Drive Fans at 2,900 rpm

High pressure fan size		اندازه فن فشار قوی						
codification:1st figure Impeller-2nd figure:inlet=A								
1st figure	1	2	3	4	5	6	7	8
ext in mm	450	500	550	610	670	740	820	900

Model A to Q	10A	10B	11D	20A	20B	21D	30A	31C
A	100	100	125	100	100	125	100	125
B	62	62	68	62	62	68	62	68
C	72	72	93	72	72	93	72	93
D	40	40	40	40	40	40	40	40
E	M8	M8	M8	M8	M8	M8	M8	M8
بر اساس قدرت الکتروموتور ابعاد آن در زمان ثبت سفارش اعلام می شود								

Model A to Q	32E	40A	41C	42E	51B	52D	53F	61B
A	150	100	125	150	125	150	175	125
B	75	62	68	75	68	75	92	68
C	120	72	93	120	93	120	130	98
D	40	50	50	50	50	50	50	50
E	M8	M8	M8	M8	M10	M10	M10	M10
بر اساس قدرت الکتروموتور ابعاد آن در زمان ثبت سفارش اعلام می شود								

Model A to Q	62D	63F	72C	73E	74G	82C	83E	84G
A	150	175	150	175	200	150	175	200
B	75	92	75	92	101	75	92	101
C	120	130	120	130	147	120	130	147
D	50	50	50	50	50	50	50	50
E	M10	M10	M10	M10	M10	M10	M10	M10
بر اساس قدرت الکتروموتور ابعاد آن در زمان ثبت سفارش اعلام می شود								

